

HP EliteDesk 800 G4 Mini BIOS Configuration

Document Version 1.1

02-October-2020

Security

- TPM Embedded Security
 - TPM Device: Hidden
 - TPM Activation Policy: No prompts
- BIOS Sure Start
 - All options unchecked
- Intel SGX: Disable

Advanced

- Boot Options
 - Startup Delay: 5. (useful during testing to give time for Function key presses)
 - Fast Boot: unchecked
 - USB Storage Boot: **checked**
 - Network (PXE) Boot: unchecked
 - Audio Alerts During Boot: unchecked (to disable beep after pressing F9 at boot)
 - UEFI Boot Order
 - USB
 - Other boot drives as desired
 - Legacy Boot Order
 - Unchecked
- HP Sure Recover
 - Unchecked
- Secure Boot Configuration
 - Legacy Support **Disable** and Secure Boot **Disable**
 - Secure Boot Key Management
 - All options unchecked
- System Options
 - Configure Storage Controller for RAID: unchecked
 - Configure Storage Controller for Intel Optane: unchecked
 - Turbo-boost: checked
 - Hyperthreading: checked
 - Multi-processor: checked
 - Virtualization Technology (VTx): checked
 - Virtualization Technology for Directed I/O (VTd): unchecked
 - M.2 SSD 1: checked
 - M.2 SSD 2: checked
 - M.2 WLAN BT (unchecked if you have Intel WLAN / BT device or don't have WLAN / BT)
 - Allow PCIe/PCI SERR# Interrupt: checked

- Power Button Override: 4 sec
 - USB Type-C Connector System Software Interface (USCI): unchecked
 - HP Application Driver: unchecked
- Built-In Device Options
 - Embedded LAN Controller: checked
 - Wake On LAN: Disabled
 - Dust Filter: Unchecked
 - Video Memory Size: ~~64MB~~ **512MB**
 - Audio Device: checked
 - Microphone: Enable
 - Internal Speakers: checked
 - Increase Idle Fan Speed (%): 0
 - M.2 USB / Bluetooth: Unchecked (disabled in System Options)
- Port Options
 - Front USB Ports: checked
 - Front USB Port 1: checked
 - Front USB Port 2: checked
 - Front USB Port 3: checked
 - Rear USB Port 1: checked
 - Rear USB Port 2: checked
 - Rear USB Port 3: checked
 - Rear USB Port 4: checked
 - USB Legacy Port Charging: unchecked
 - Front USB Type-C Downstream Charging: unchecked
 - SATA 0: checked
 - Restrict USB Devices: Allow all USB Devices
- Option ROM Launch Policy
 - This is grayed out for me (probably as a result of another selection)
- Power Management Options
 - Runtime Power Management: checked
 - Extended Idle Power States: checked
 - S5 Maximum Power Savings: checked
 - SATA Power Management: checked
 - PCI Express Power Management: checked
 - Power On from Keyboard Ports: this option is grayed out for me
 - Unique Sleep State Blink Rates: unchecked
- Remote Management Options
 - Intel Management Engine (ME): checked (required for proper UHD 630 Sleep / Wake)
 - Intel Active Management Technology (AMT): unchecked