

BIOS Settings for the Gigabyte GA-P35-DS3L motherboard with F7 BIOS
BIOS Settings for the Gigabyte GA-EP35-DS3L motherboard with F5 BIOS

Standard CMOS Features:

Date: [set]
Time: [set]
Drive A: [None]
Floppy 3 Mode Support: [Disabled]
Halt On: [No Errors]

Advanced BIOS Features:

Hard Disk boot Priority: [set your boot drive as #1]
First Boot Device: [CDROM]
Second Boot Device: [Hard Disk]
Third Boot Device: [Disabled]
Password Check: [setup if desired]
HDD S.M.A.R.T. Capability: [Enabled]
Limit CUID Max. to 3: [Disabled]
No-Execute Memory Protect: [Enabled]
CPU Enhanced Halt (C1E): [Enabled]
CPU Thermal Monitor 2(TM2): [Enabled]
CPU EIST Function: [Enabled]
Full Screen LOGO Show: [Disabled]
Init Display First: [PEG]

Integrated Peripherals:

SATA RAID/AHCI Mode: [AHCI]
SATA Port0-3 Native mode: [Disabled]
USB Controller: [Enabled]
USB 2.0 Controller: [Enabled]
USB Keyboard Support: [Enabled]
USB Mouse Support: [Enabled]
Legacy USB storage detect: [Enabled]
Azalia Codec: [Auto] * *Disable this if you are using a separate sound card*
Onboard H/W LAN: [Enabled] * *Disable this if you are using a separate network card*
SMART LAN: [Ignore]
Onboard LAN Boot ROM: [Disabled]
Onboard IDE Controller: [Disabled]
Onboard Serial Port 1: [Disabled]
Onboard Parallel Port: [Disabled]

Power Management Setup:

ACPI Suspend Type: [S3(STR)]
Soft-Off by PWR-BTTN: [Instant-Off]
PME Event Wake Up: [Disabled]
Power On by Ring: [Disabled]
Resume by Alarm: [Disabled]
HPET Support: [Enabled]
HPET Mode: [64-bit mode]
Power On By Mouse: [Disabled]
Power On By Keyboard: [Disabled]
AC Back Function: [Soft-Off]

MB Intelligent Tweaker (M.I.T.)

CPU Clock Ratio: [9x] * *8x may be the default, so be sure to update to whichever multiplier matches your CPU*